United States Patent [19]

Garay et al.

[11] **Patent Number: 4,772,895**

[45] **Date of Patent: Sep. 20, 1988**

[54] **WIDE-BAND HELICAL ANTENNA**

[75] Inventors: **Oscar M. Garay**, North Lauderdale; **Quirino Balzano**, Plantation, both of Fla.

[73] Assignee: **Motorola, Inc.**, Schaumburg, Ill.

[21] Appl. No.: **61,504**

[22] Filed: **Jun. 15, 1987**

[51] **Int. Cl.**[4] **H01Q 1/36**

[52] **U.S. Cl.** **343/895**; 343/752

[58] **Field of Search** 343/895, 790, 791, 749, 343/752, 827

[56] **References Cited**

U.S. PATENT DOCUMENTS

2,503,010	4/1950	Tiley	343/895
2,611,868	9/1952	Marston et al.	343/895
2,996,718	8/1961	Foley	343/825
3,852,759	12/1974	Felsenheld et al.	343/729
4,137,534	1/1979	Goodnight	343/752
4,148,030	4/1979	Foldes	343/895
4,169,267	9/1979	Wong et al.	343/895
4,229,743	10/1980	Vo et al.	343/749
4,442,438	4/1984	Siwiak et al.	343/792
4,490,727	12/1984	Kowols	343/895

Primary Examiner—William L. Sikes
Assistant Examiner—Hoanganh Le
Attorney, Agent, or Firm—Mark P. Kahler

[57] **ABSTRACT**

An antenna is provided which includes first and second helical elements which are separated by a dielectric spacer. The first helical element is fed a radio frequency driving signal and the remaining second element is coupled to ground. The first and second elements are coupled together in a fashion which results in a dramatic increase in antenna bandwidth in comparison to prior helical antennas.

4 Claims, 4 Drawing Sheets





FIG. 1A
—PRIOR ART—



FIG. 1B
—PRIOR ART—



FIG. 2A
—PRIOR ART—



FIG. 2B
—PRIOR ART—



FIG. 3


FIG. 4A
20B
L2
L1
20
20A
10
14
12
FIG. 4B
20
30
L3
FIG. 4C
20
40B
30
L4
40
40A



FIG. 5

WIDE-BAND HELICAL ANTENNA

BACKGROUND OF THE INVENTION

This invention relates in general to antennas for radiating electromagnetic signals. More particularly, the invention relates to helical antennas for portable radios and other communications equipment.

In the past, relatively large antennas such as the half wave dipole depicted in FIG. 1A were quite acceptable as antennas for low frequency fixed station transceivers. Such half-wave dipole antennas typically exhibit a reasonably broad bandwidth, as illustrated in the return loss vs. frequency graph of FIG. 1B. Unfortunately, if used on a hand-held portable radio, such a half-wave dipole is generally relatively large with respect to the size of the portable radio. The large size of such a dipole antenna often makes it undesirable for portable radio applications.

One solution to the above antenna size problem is to form each of the two quarter wave ($\lambda/4$) elements of the antenna of FIG. 1A into respective helices thus resulting in the helical antenna of FIG. 2A. Each helical element thus formed occupies significantly less space ($\lambda'/4$) than the corresponding element of the dipole of FIG. 1A, but desirably exhibits the same effective electrical length. Although such a helical antenna does result in a decrease in the effective height of the antenna structure employed on a portable radio, the usable bandwidth of the antenna is significantly less than that of the dipole antenna of FIG. 1A. This reduction of usable bandwidth is readily seen in the return loss vs. frequency graph of FIG. 2B for the antenna of FIG. 2A. Moreover, FIG. 3 shows a Smith Chart of the driving point impedance of the antenna of FIG. 2A which demonstrates the narrow banded nature of such a helical antenna.

Those skilled in the antenna arts appreciate that helical antennas generally exhibit a narrow bandwidth. This causes a problem when a particular portable radio is to operate over a relatively wide band of frequencies. For example, to cover the VHF band between 136 and 174 MHz, three or more conventional helical antennas cut to different frequencies must often be used.

BRIEF SUMMARY OF THE INVENTION

One object of the present invention is to provide an antenna which is sufficiently small to be used on portable radio devices.

Another object of the invention is to provide a antenna which is relatively small and yet exhibits a relatively wide bandwidth.

In one embodiment of the invention, an antenna is provided which includes a feed port with a signal feed portion and a ground portion. The antenna further includes a first helically configured conductive element having opposed ends, one end of which is coupled to the signal feed portion of the feed port. A second helically configured conductive element having opposed ends is wound around a portion of said first element. One end of the second element is coupled to the ground portion of the feed port. A spacer is situated between the first and second helical elements to electrically insulate the first and second elements. The spacer is sufficiently thin such that the first element is tightly coupled to the second element so as to broaden the frequency response exhibited by the first element.

The features of the invention believed to be novel are specifically set forth in the appended claims. However, the invention itself, both as to its structure and method of operation, may best be understood by referring to the following description and the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1A is a representation of a conventional half-wave dipole antenna.

FIG. 1B is a return loss vs. frequency graph of the antenna of FIG. 1A.

FIG. 2A is a representation of a half-wave helical antenna.

FIG. 2B is a return loss vs. frequency graph of the antenna of FIG. 2A.

FIG. 3 is a Smith Chart plot of the driving point impedance of a conventional helical dipole antenna such as the antenna of FIG. 2A.

FIG. 4A is a representation of the helical antenna of the present invention in an early stage of fabrication.

FIG. 4B is a representation of the helical antenna of the invention in a more advanced stage of fabrication.

FIG. 4C is a representation of the helical antenna of the invention.

FIG. 5 is a Smith Chart plot of the driving point impedance of the helical antenna of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

Turning now to FIG. 4A, one embodiment of the antenna of the present invention is shown in an early stage of fabrication. Although the particular antenna disclosed herein operates in the 136–174 MHz VHF band and exhibits a center frequency of 155 MHz, those skilled in the art will appreciate that the dimensions which follow are given for purposes of example and may be scaled so that the antenna of the invention will operate in other frequency ranges as well.

The antenna of FIG. 4A includes a coaxial connector **10** having a center conductor **12** and a ground **14**. The antenna further includes a primary resonator or element **20** having ends **20A** and **20B**, of which end **20A** is coupled to the center conductor **12** of coaxial connector **10**. End **20A** and ground **14** together form the feedpoint of the antenna. Primary element **20** is helically wound as shown in FIG. 4A. The electrical length of element **20** is selected to be approximately 25% less than $\lambda/4$ wherein λ is the wavelength corresponding to the desired center frequency of the antenna. In this particular example, the dimensions of primary element **20** are selected such that element **20** resonates at approximately 115 MHz. Element **20** exhibits a physical length **L1** wherein **L1** is 22 cm in this example. The diameter **L2** of element **20** is approximately 7 mm. The helix formed by element **20** exhibits a pitch of approximately 3.2 turns per cm (approximately 8 turns per inch) in this example.

A cylindrical dielectric spacer **30** is situated over the lower portion of element **20** near connector **10** as shown in FIG. 4B. Spacer **30** is coaxially situated with respect to element **20**. The length, **L3**, of spacer **30** is selected to be sufficiently long to insulate secondary element **40** (described later in the discussion of FIG. 4C) from primary element **20**. For example, in this embodiment **L3** is approximately 7 cm. Spacer **30** is fabricated from low dielectric constant materials such as plastic, insula-

tive shrink tubing material, Teflon TM material or other similar electrically insulative materials.

FIG. 4C shows the assembled antenna as including a secondary resonator or element **40** having ends **40A** and **40B**. Secondary element end **40A** is coupled to the ground portion **14** of connector **10**. Secondary element **40** is helically wound around primary element **20** and spacer **30** as shown. In one embodiment of the antenna, the pitch of primary element **20** is approximately twice that of secondary element **40**. That is, primary element **20** exhibits approximately twice as many turns per cm as secondary element **40**. For example, in this embodiment of the antenna, the pitch of element **40** is approximately 1.6 turns per cm (approximately 4 turns per inch). It is noted that secondary element **40** is coaxially aligned with respect to primary element **20**. It is further noted that primary element **20** is substantially longer than secondary element **40** as described in more detail subsequently.

The thickness of spacer **30** is selected to be sufficiently small such that secondary element **40** is tightly coupled, capacitively and inductively, to primary element **20**. For example, thicknesses of spacer **30** (outer diameter minus inner diameter) within the range of approximately 0.25 mm to approximately 0.3 mm will perform acceptably although thicknesses of spacer **30** somewhat smaller or larger than this range will perform acceptably as long as tight coupling between primary element **20** and secondary element **40** is maintained.

The physical length, L4, of secondary element **40** is equal to approximately 7 cm in this example. The electrical length of secondary element **40** is selected to be approximately equal to one third of the electrical length of primary element **20**. Stated alternatively, the resonant frequency of secondary element **40** is approximately three times the resonant frequency of primary element **20**. For example, in the present embodiment, primary element **20** is cut to a length **L1** which exhibits a resonant frequency of approximately 115 MHz and secondary element **40** is cut to a length **L4** which exhibits a resonant frequency of approximately 356 MHz. It is noted that when the resonant frequency of elements **20** or **40** is discussed, we are referring to resonant frequency of each element by itself in free space. That is, such resonance is determined by measuring the resonant frequency of each element prior to assembly of the antenna. In this manner, the resonant frequency of the element is determined prior to coupling to other structures. As described above, it has been found that tightly coupling secondary element **40** to primary element **20** in the region of the feedpoint results in an antenna which exhibits a center frequency of 155 MHz and which exhibits significantly increased bandwidth (20% bandwidth at 10 dB return loss).

It was found that the pitch and the length L4 of secondary element **40** affect the degree of coupling between primary element **20** and secondary element **40**. That is, increasing the pitch (turns per cm) of secondary element **40** increases the coupling between primary element **20** and secondary element **40**. It is also noted that increasing the length L4 of secondary element **40** increases the coupling between primary element **20** an secondary element **40**. Those skilled in the antenna arts will appreciate that the pitch of element **40** and length L4 of element **40** may be varied from the dimensions given. It was found that for the 155 MHz center frequency antenna example discussed above, secondary element **40** may exhibit pitches within the range of approximately 1.4 turns per cm to approximately 1.8 turns per cm, although other pitches may be employed providing elements **20** and **40** remain tightly coupled. Generally, if the length L4 of secondary element **40** is increased or decreased, then the length of primary element **20** is should be similarly increased or decreased to compensate for the change in length. The alteration of the lengths of elements **20** and **40** will generally change the center frequency of the antenna.

A housing of soft rubber or similar material (not shown) may be molded or otherwise used to cover the antenna of FIG. 4C in the same manner that such housings are used in other "rubber duck" type antennas employed on portable radios. Those skilled in the antenna arts are very familiar with the application of such housings to helical antennas. Since the antenna performs best when the dielectric material within primary element **20** is air, care should be taken when a housing is molded onto the antenna of FIG. 4C that the molding material does not enter the interior of primary element **20**.

FIG. **5** is a Smith Chart of the driving point impedance of the antenna of FIG. 4C. The center point of the Smith Chart is located at **50** and corresponds to 50 ohms. The plotted circle **60** represents the 2:1 SWR (standing wave ratio) circle. That is, all points within circle **60** exhibit an acceptable SWR which is less that 2:1. Curve **70** is the actual plot of the driving point impedance vs. frequency for the antenna of FIG. 4C. It is noted that for frequencies between 135 MHz and 170 MHz, the SWR remains less than 2:1 which indicates a significantly more broadband antenna than the conventional helical antenna whose driving point impedance as a function of frequency was illustrated in FIG. **3**.

The foregoing describes an antenna which is sufficiently small to be used on portable radio devices. Despite the small size of the antenna, it exhibits a relatively wide bandwidth.

While only certain preferred features of the invention have been shown by way of illustration, many modifications and changes will occur to those skilled in the art. For example, it was also found that for the 155 MHz center frequency antenna example discussed above, primary element **40** may exhibit a physical length **L1** different than that of the example. Those skilled in the antenna arts will appreciate that if a longer primary element **40** is desired, then secondary element **40** (L4) is appropriately lengthened as well. Other modifications are also possible keeping within the spirit of the invention. For example, while it is generally desirable to have the thickness (outer diameter minus inner diameter) of spacer **30** be as small as possible to maximize the coupling between primary element **20** and secondary element **40**, the thickness of spacer **30** may be somewhat larger than in the example above. However, as the thickness of spacer **30** is increased, the length and pitch of element **40** should be increased to compensate for the loss of coupling between element **20** and element **40** which would otherwise occur.

Those skilled in the art also appreciate that although in the above example, the center frequency of the antenna is 155 MHz the dimensions of the antenna may be scaled up or down to fabricate an antenna which exhibits a center frequency which is less than or greater than 155 MHz as desired. These and other modifications will become apparent to those skilled in the art. It is, therefore, to be understood that the present claims are in-

tended to cover all such modifications and changes which fall within the true spirit of the invention.

We claim:

1. An antenna comprising:

a feed port including a signal feed portion and a ground portion;

a first helically configured conductive element having opposed ends and exhibiting a first pitch and a first electrical length, one end of said first element being coupled to the signal feed portion of said feed port;

a second helically configured conductive element having opposed ends, and exhibiting a second pitch and a second electrical length, said second element being coaxially wound around a portion of said first element, one end of said second element being coupled to the ground portion of said feed port, said second pitch being equal to approximately one half of said first pitch, said second electrical length being equal to approximately one third of said first electrical length, and

cylindrical spacer means, coaxially situated between said first and second elements, for electrically insulating said first and second elements, said spacer means being sufficiently thin such that said first element is tightly coupled to said second element so as to broaden the frequency response exhibited by said first element.

2. The antenna of claim 1 wherein said spacer means is comprised of dielectric material.

3. The antenna of claim 1 wherein the length of said second element is selected such that said second element exhibits a resonance offset in frequency from the resonance of said first element.

4. The antenna of claim 1 wherein the second element resonates at a frequency approximately three times the resonant frequency of the first element.

* * * * *